



Logitech K750 Keyboard Battery Replacement

How to replace a dead or worn out battery in a Logitech K750 Solar keyboard.

Written By: Carsten Frauenheim



INTRODUCTION

Use this guide to safely remove and replace the battery in a Logitech K750 Solar wireless keyboard.

Note: The K750 Solar requires a rechargeable **ML2032** coin cell battery as a replacement. Although it's the same size and shape as the more common CR2032, CR2032s are not rechargeable. You can also use a LIR2032 rechargeable battery as well.



TOOLS:

- [Spudger](#) (1)



PARTS:

- [LIR2032 Lithium Ion Rechargeable Batteries](#) (1)

Step 1 — Turn off the keyboard



- Before you begin, flip the keyboard's power switch into the **OFF** position.

Step 2 — Flip the keyboard over



- Flip the entire keyboard over, keys facing down.

Step 3 — Pry open the battery tray



- ⓘ The ML2032 rechargeable coin cell battery is located in a tray at the back edge of the keyboard.
- Insert the flat end of a spudger into the gap between the battery tray and the top surface of the keyboard.
- Pivot the spudger down, towards the top of the keyboard, to begin to pry the tray out of its cavity.

Step 4 — Remove the battery tray



- Use the flat end of the spudger to push the battery tray out and away from the keyboard.
- ⓘ The tray is held in by small "ears" and may take a significant amount of force to dislodge.
- Remove the battery tray.
- ☑ During reassembly, firmly push the battery tray into its slot until it clicks into place.

Step 5 — Remove the battery



- Push the battery out of the tray to remove it.
 - ⓘ Note the battery orientation—it can only go in one way. Set the battery into the tray with side with the text and the "+" sign facing down.
- ⚠ Use only a rechargeable **ML2032** coin cell battery as a replacement. Although it's the same size and shape as the more common **CR2032**, CR2032s are not rechargeable.**

To reassemble your device, follow the above steps in reverse order.

Take your e-waste to an [R2 or e-Stewards certified recycler](#).

Repair didn't go as planned? Check out our [Answers community](#) for troubleshooting help.