



# Huawei Union Motherboard Replacement

This guide will show you how to replace the Motherboard for the Huawei Union in a few short and simple steps.

Written By: Brittany Achor



---

## INTRODUCTION

Use this guide if your Huawei Union will not charge when plugged into a charger or begins losing charge faster than previously observed.

---



### TOOLS:

- [Spudger](#) (1)
  - [Phillips #00 Screwdriver](#) (1)
  - [Magnetic Project Mat](#) (1)
-

## Step 1 — Battery



- Wedge your thumb nail, or the flat end of a spudger, into the bottom left corner and pry off.

## Step 2



- Use the flat end of a spudger, or fingernail, to lift up the battery and pull out.



## Step 3 — Camera Lens Panel



- Remove the thirteen 3mm Phillips #00 screws from the back panel.

## Step 4



- Use the flat end of a spudger to pry off the back panel.

## Step 5 — Motherboard



- Remove a single 3mm Phillips #00 screw from the motherboard.

## Step 6



- Using the flat end of a spudger to disconnect the motherboard ribbon cable.



## Step 7



- Firmly hold the second ribbon cable's plastic film cover and pull up to disconnect.

## Step 8



- Wedge the flat end of a spudger underneath the motherboard and pry upwards to separate it from the frame.

To reassemble your device, follow these instructions in reverse order.

This document was generated on 2020-11-28 06:38:58 AM (MST).

